



Типоразмер	Количество полюсов	Габаритные размеры, мм				Установочные и присоединительные размеры, мм																	
		I30	h31	d30	d24	b10	b11	I10	I11	I31	d1	I1	b1	h5	h1	h	d10	d20	d25	I20	d22	n	
		L	HD	AC	P	A	AB	B	BB	C	D	E	F	GA	GD	H	K	M	N	T	S	n	
АИР56А	2, 4	202	160	113	140	90	113	71	90	36	11	23	4	12.5	4	56	5.8	115	95	3	10	4	
АИР56В		202	160	113	140	90	113	71	90	36	11	23	4	12.5	4	56	5.8	155	95	3	10	4	
АИР63А	2, 4, 6	250	170	140	160	100	124	80	102	40	14	30	5	16	5	63	5.8	130	110	3.5	10	4	
АИР63В		250	170	140	160	100	124	80	102	40	14	30	5	16	5	63	5.8	130	110	3.5	10	4	
АИР71А	2, 4, 6	290	200	158	200	112	130	90	110	45	19	40	6	21.5	6	71	7	165	130	3.5	12	4	
АИР71В	2, 4, 6, 8	290	200	158	200	112	130	90	110	45	19	40	6	21.5	6	71	7	165	130	3.5	12	4	
АИР80МА	2, 4, 6, 8	311	212	155	200	125	160	100	131	50	22	50	6	24.5	6	80	10	165	130	3.5	12	4	
АИР80МВ		343	212	155	200	125	160	100	140	50	22	50	6	24.5	6	80	10	165	130	3.5	12	4	
АИР90ЛА	2, 4, 6	376	235	174	250	140	176	125	170	56	24	50	8	27	7	90	10	215	180	4	15	4	
АИР90А	8	376	235	174	250	140	176	125	170	56	24	50	8	27	7	90	10	215	180	4	15	4	
АИР90В	8	376	235	174	250	140	176	125	170	56	24	50	8	27	7	90	10	215	180	4	15	4	
АИР100С	2, 4	382	256	195	250	160	205	112	175	63	28	60	8	31	7	100	12	215	180	4	15	4	
АИР100Л	2, 4, 6, 8	420	256	195	250	160	205	140	185	63	28	60	8	31	7	100	12	215	180	4	15	4	
АИР112МА	2, 4, 6, 8	462	295	216	300	190	240	140	195	70	32	80	10	35	8	112	12	265	230	4	15	4	
АИР112МВ	6, 8	462	295	216	300	190	240	140	195	70	32	80	10	35	8	112	12	265	230	4	15	4	
АИР132С	4, 6, 8	472	334	255	350	216	270	140	198	89	38	80	10	41	8	132	12	300	250	5	19	4	
АИР132М	2, 4, 6, 8	510	334	255	350	216	270	178	235	89	38	80	10	41	8	132	12	300	250	5	19	4	
АИР160С	2	620	410	313	350	254	320	178	314	108	42	110	12	45	8	160	15	300	250	5	19	4	
АИР160М	4, 6, 8	620	410	313	350	254	320	178	314	108	48	110	14	51.5	9	160	15	300	250	5	19	4	
АИР160М	2	663	410	313	350	254	320	210	314	108	42	110	12	45	8	160	15	300	250	5	19	4	
АИР160М	4, 6, 8	663	410	313	350	254	320	210	314	108	48	110	14	51.5	9	160	15	300	250	5	19	4	
АИР180С	2	687	455	356	400	279	355	203	311	121	48	110	14	51.5	9	180	15	350	300	5	19	4	
АИР180С	4	687	455	356	400	279	355	203	311	121	55	110	16	59	10	180	15	350	300	5	19	4	
АИР180М	2	725	455	356	400	279	355	241	354	121	48	110	14	51.5	9	180	15	350	300	5	19	4	
АИР180М	4, 6, 8	725	455	356	400	279	355	241	354	121	55	110	16	59	10	180	15	350	300	5	19	4	
АИР200М	2	781	480	395	450	318	395	267	379	133	55	110	16	59	10	200	19	400	350	5	19	8	
АИР200М	4, 6, 8	811	480	395	450	318	395	267	379	133	60	140	18	64	11	200	19	400	350	5	19	8	
АИР200Л	2	781	480	395	450	318	395	305	379	133	55	110	16	59	10	200	19	400	350	5	19	8	
АИР200Л	4, 6, 8	811	480	395	450	318	395	305	379	133	60	140	18	64	11	200	19	400	350	5	19	8	

Рисунок 1. Габаритные и установочные размеры двигателей монтажного исполнения IM 2081